



6609 APOLLO

7 Kukush Str. Sofia 1309, Bulgaria, tel: +359 2 8129328; fax: +359 2 8129440
www.casino-technology.com

SAFETY

APOLLO

All rights reserved!

Casino Technology AD may alter any part of this manual without prior notification.

| | | |
|--|--|--|
|  | 6609 APOLLO | |
| | 7 Kukush Str. Sofia 1309, Bulgaria, tel: +359 2 8129328; fax: +359 2 8129440 www.casino-technology.com | |

General Issues

This Safety Guide contains important instructions that should be followed during installation, operation and maintenance of 6609 APOLLO casino gaming equipment. It is intended for customers who setup, install, relocate, or maintain the equipment.

WARNINNG! Improper handling of the equipment forfeits Casino Technology AD obligations under warranty!

Handling Safety

To avoid condensing, the machine should be unpacked and kept in the operational environmental conditions at least 4 (four) hours after transportation.

Prior to plug in the machine to the Mains, make a visual check of the cabinet and power supply cable for mechanical damage and ensure proper grounding. Also check for any dismounted parts inside the cabinet. Check also the Mains voltage and wiring to be compatible to the machine specification.

Prior to put the machine in operation, check if the game statistics is cleared and verify the software settings.

Prior to plug in the equipment check that the power cable(s), plug(s), and sockets are in good condition (no scratches or any other mechanical damages on the power cord).

It is NOT recommended to place the machine on carpets or other floor covering which collects electrostatic charge. The cooling openings in the cabinet should NOT be covered. The gaming machine is supposed for indoor use ONLY.

Do not connect additional power consumers to the power supply of the equipment. Always consult the additional consumers with manufacturer of the equipment

Avoid equipment placement close to any liquid sources, or heating systems and/or devices!

Spilling liquids on the equipment is prohibited regardless of the equipment is turned on or off! If this happens, turn off the machine and call for technician.

| | | |
|--|--|--|
|  | 6609 APOLLO | |
| | 7 Kukush Str. Sofia 1309, Bulgaria, tel: +359 2 8129328; fax: +359 2 8129440 www.casino-technology.com | |

Cleaning the equipment with wet cloth is prohibited regardless of the equipment is turned on or off!

Cleaning is done ONLY when the equipment is turned.

Attention! It is not allowed the machine to be placed outdoors, under direct sun rays, close to high power transformers, electrical engines and welding devices.

The machine can be carried by any transport means, if the rules for appropriate transport are observed.

Air transport of the gaming machines is carried out in warm hermetic premises.

Transportation in containers is allowed.

Transportation of unpacked machines is allowed, if they are protected from atmospheric impacts as rainfalls, dust, sun radiation, etc.

During loading and fixing the machines in the transport means, they should be placed in steady position, protected from shifts and shocks during transportation.

Transportation of the machine in horizontal position is NOT ALLOWED!

The gaming machine should be stored in warehouses in the environment, free from active chemical ingredients. The temperature inside the warehouse premises should be maintained between + 5 and +35°C at relative humidity approx. 85% without high fluctuations. The machines should be stored at least 1 m away from heating installations.

Electrical Safety

To avoid accidents, it is FORBIDDEN:

To plug the machine in the Mains outlet without grounding

To switch on the machine with opened doors and/or covers or without glasses

| | | |
|--|--|--|
|  | 6609 APOLLO | |
| | 7 Kukush Str. Sofia 1309, Bulgaria, tel: +359 2 8129328; fax: +359 2 8129440 www.casino-technology.com | |

To replace fuses or to fulfill repair or service actions in the machine connected to the Mains

To use non-standard or self-made fuses

To leave the machine without control

To use self made power cords

Remark: ONLY the disconnected mains power cord will guarantee no risk of electrical shock!

The Mains plug-in should be located at the convenient place, allowing easy switch off the machine in case of accident.

DO NOT close ventilation holes of the cabinet and do not impede its natural ventilation. At the rear of the cabinet there should be a space of at least 5 cm, and at the both sides (between two cabinets) the space should be at least 20 cm.

The gaming machine servicing should be maintained by qualified staff, certified to work with electrical voltage up to 1000 V.

In case of fire, the machine should be immediately unplugged from the Mains. To put out the fire use thick cloth or fire-extinguisher with carbon dioxide.

IMPORTANT

It is strictly prohibited to open the doors or undertake other actions over the cabinets of Casino Technology AD. All repair works are fulfilled only by the qualified persons or in the authorized service center of Casino Technology.